

**Picoamp Input Current,
Microvolt Offset,
Low Noise Op Amp**

FEATURES

- OP-07 Type Performance:
at 1/8th of OP-07's Supply Current
at 1/20th of OP-07's Bias and Offset Currents
- **Guaranteed Offset Voltage:** 25 μ V Max
- **Guaranteed Bias Current:** 100pA Max
- **Guaranteed Drift:** 0.6 μ V/ $^{\circ}$ C Max
- Low Noise, 0.1Hz to 10Hz: 0.5 μ V_{P-P}
- **Guaranteed Low Supply Current:** 500 μ A Max
- **Guaranteed CMRR:** 114dB Min
- **Guaranteed PSRR:** 114dB Min
- **Guaranteed Operation at \pm 1.2V Supplies**

APPLICATIONS

- Replaces OP-07 While Saving Power
- Precision Instrumentation
- Charge Integrators
- Wide Dynamic Range Logarithmic Amplifiers
- Light Meters
- Low Frequency Active Filters
- Thermocouple Amplifiers

DESCRIPTION


The LT®1012 is an internally compensated universal precision operational amplifier which can be used in practically all precision applications. The LT1012 combines picoampere bias currents (which are maintained over the full -55°C to 125°C temperature range), microvolt offset voltage (and low drift with time and temperature), low voltage and current noise, and low power dissipation. The LT1012 achieves precision operation on two Ni-Cad batteries with 1mW of power dissipation. Extremely high common mode and power supply rejection ratios, practically unmeasurable warm-up drift, and the ability to deliver 5mA load current with a voltage gain of one million round out the LT1012's superb precision specifications.

The all around excellence of the LT1012 eliminates the necessity of the time consuming error analysis procedure of precision system design in many applications; the LT1012 can be stocked as the universal internally compensated precision op amp.

L, LTC and LT are registered trademarks of Linear Technology Corporation.
Protected by U.S. patents 4,575,685 and 4,775,884

TYPICAL APPLICATION

\pm 250V Common Mode Range Instrumentation Amplifier ($A_V = 1$)



COMMON MODE REJECTION RATIO = 74dB (RESISTOR LIMITED)
WITH OPTIONAL TRIM = 130dB


OUTPUT OFFSET (TRIMMABLE TO ZERO) = 500 μ V

OUTPUT OFFSET DRIFT = 10 μ V/ $^{\circ}$ C

INPUT RESISTANCE = 1M

LT1012A • TA01

Typical Distribution of Input Offset Voltage



LT1012A • TA02

sn1012 1012afbs




LT1012A/LT1012

ABSOLUTE MAXIMUM RATINGS

(Note 1)

Supply Voltage	±20V	Operating Temperature Range
Differential Input Current (Note 1)	±10mA	LT1012AM/LT1012M (OBSOLETE)	-55°C to 125°C
Input Voltage	±20V	LT1012I/LT1012AI	-40°C to 85°C
Output Short Circuit Duration	Indefinite	LT1012AC/LT1012C	
			LT1012D/LT1012S8	0°C to 70°C
			Storage Temperature Range	-65°C to 150°C
			Lead Temperature (Soldering, 10 sec)	300°C

PACKAGE/ORDER INFORMATION

 TOP VIEW S8 PACKAGE 8-LEAD PLASTIC SO $T_{JMAX} = 100^\circ\text{C}$, $\theta_{JA} = 170^\circ\text{C/W}$	 TOP VIEW H PACKAGE 8-LEAD TO-5 METAL CAN $T_{JMAX} = 150^\circ\text{C}$, $\theta_{JA} = 150^\circ\text{C/W}$, $\theta_{JC} = 45^\circ\text{C/W}$	 TOP VIEW N8 PACKAGE 8-LEAD PDIP $T_{JMAX} = 100^\circ\text{C}$, $\theta_{JA} = 130^\circ\text{C/W}$
ORDER PART NUMBER	ORDER PART NUMBER	ORDER PART NUMBER
LT1012S8 LT1012IS8 LT1012ACS8 LT1012AIS8	LT1012AMH LT1012MH LT1012ACH LT1012CH LT1012DH	LT1012ACN8 LT1012AIN8 LT1012CN8 LT1012DN8 LT1012IN8
S8 PART MARKING	OBSOLETE PACKAGE Consider the S8 or N8 Packages for Alternate Source	
1012 1012I 1012A 1012AI		

Consult LTC Marketing for parts specified with wider operating temperature ranges.

LT1012A/LT1012

ELECTRICAL CHARACTERISTICS

$V_S = \pm 15V$, $V_{CM} = 0V$, $T_A = 25^\circ C$, unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	LT1012AM/AC/AI			LT1012M/I			LT1012C			UNITS
			MIN	TYP	MAX	MIN	TYP	MAX	MIN	TYP	MAX	
V_{OS}	Input Offset Voltage	(Note 3)	8 20	25 90	8 20	35 90	10 25	50 120	μV μV			
	Long Term Input Offset Voltage Stability			0.3		0.3		0.3				$\mu V/\text{month}$
I_{OS}	Input Offset Current	(Note 3)	15 25	100 150		15 25	100 150		20 30	150 200		pA pA
I_B	Input Bias Current	(Note 3)	± 25 ± 35	± 100 ± 150		± 25 ± 35	± 100 ± 150		± 30 ± 40	± 150 ± 200		pA pA
e_n	Input Noise Voltage	0.1Hz to 10Hz		0.5			0.5		0.5			μV_{P-P}
e_n	Input Noise Voltage Density	$f_0 = 10\text{Hz}$ (Note 4) $f_0 = 1000\text{Hz}$ (Note 5)	17 14	30 22		17 14	30 22		17 14	30 22		$nV\sqrt{\text{Hz}}$ $nV\sqrt{\text{Hz}}$
i_n	Input Noise Current Density	$f_0 = 10\text{Hz}$		20			20		20			$fA/\sqrt{\text{Hz}}$
A_{VOL}	Large Signal Voltage Gain	$V_{OUT} = \pm 12V$, $R_L \geq 10k\Omega$ $V_{OUT} = \pm 10V$, $R_L \geq 2k\Omega$	300 300	2000 1000		300 200	2000 1000		200 200	2000 1000		V/mV V/mV
CMRR	Common Mode Rejection Ratio	$V_{CM} = \pm 13.5V$	114	132		114	132		110	132		dB
PSRR	Power Supply Rejection Ratio	$V_S = \pm 1.2V$ to $\pm 20V$	114	132		114	132		110	132		dB
	Input Voltage Range		± 13.5	± 14		± 13.5	± 14		± 13.5	± 14		V
V_{OUT}	Output Voltage Swing	$R_L = 10k\Omega$	± 13	± 14		± 13	± 14		± 13	± 14		V
	Slew Rate		0.1	0.2		0.1	0.2		0.1	0.2		$V/\mu s$
I_S	Supply Current	(Note 3)		370 380	500 600		380 380	600		380 380	600	μA μA

sn1012 1012afbs

LT1012A/LT1012

ELECTRICAL CHARACTERISTICS

$V_S = \pm 15V$, $V_{CM} = 0V$, $T_A = 25^\circ C$, unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	LT1012D			LT1012S8			UNITS
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{OS}	Input Offset Voltage	(Note 3)		12 25	60		15 25	120 180	μV μV
	Long Term Input Offset Voltage Stability			0.3			0.4		$\mu V/\text{month}$
I_{OS}	Input Offset Current	(Note 3)		20 30	150		50 60	280 380	pA pA
I_B	Input Bias Current	(Note 3)		± 30 ± 40	± 150		± 80 ± 120	± 300 ± 400	pA pA
e_n	Input Noise Voltage	0.1Hz to 10Hz		0.5			0.5		μV_{P-P}
e_n	Input Noise Voltage Density	$f_0 = 10\text{Hz}$ (Note 5) $f_0 = 1000\text{Hz}$ (Note 5)		17 14	30 22		17 14	30 22	$nV/\sqrt{\text{Hz}}$ $nV/\sqrt{\text{Hz}}$
i_n	Input Noise Current Density	$f_0 = 10\text{Hz}$		20			20		$fA/\sqrt{\text{Hz}}$
A_{VOL}	Large-Signal Voltage Gain	$V_{OUT} = \pm 12V, R_L \geq 10k\Omega$ $V_{OUT} = \pm 10V, R_L \geq 2k\Omega$	200 200	2000 1000		200 120	2000 1000		V/mV V/mV
CMRR	Common Mode Rejection Ratio	$V_{CM} = \pm 13.5V$	110	132		110	132		dB
PSRR	Power Supply Rejection Ratio	$V_S = \pm 1.2V$ to $\pm 20V$	110	132		110	132		dB
	Input Voltage Range			± 13.5	± 14.0		± 13.5	± 14.0	V
V_{OUT}	Output Voltage Swing	$R_L = 10k\Omega$		± 13	± 14		± 13	± 14	V
	Slew Rate			0.1	0.2		0.1	0.2	$V/\mu s$
I_S	Supply Current	(Note 3)		380	600		380	600	μA

sn1012 1012afbs

ELECTRICAL CHARACTERISTICS

The ● denotes the specifications which apply over the full operating temperature range of $-55^{\circ}\text{C} \leq T_A \leq 125^{\circ}\text{C}$ for LT1012AM and LT1012M, and $-40^{\circ}\text{C} \leq T_A \leq 85^{\circ}\text{C}$ for LT1012AI and LT1012I.
 $V_S = \pm 15\text{V}$, $V_{CM} = 0\text{V}$, unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	LT1012AM/AI			LT1012M/I			UNITS
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{OS}	Input Offset Voltage	(Note 3)	●	30	60	30	180	μV	μV
			●	40	180	40	250	μV	
I_{OS}	Average Temperature Coefficient of Input Offset Voltage		●	0.2	0.6	0.2	1.5	$\mu\text{V}/^{\circ}\text{C}$	
I_B	Input Offset Current	(Note 3)	●	30	250	30	250	pA	pA
			●	70	350	70	350	pA	
I_B	Average Temperature Coefficient of Input Offset Current		●	0.3	2.5	0.3	2.5	$\text{pA}/^{\circ}\text{C}$	
A_{VOL}	Input Bias Current	(Note 3)	●	± 80	± 600	± 80	± 600	pA	pA
			●	± 150	± 800	± 150	± 800	pA	
A_{VOL}	Average Temperature Coefficient of Input Bias Current		●	0.6	6.0	0.6	6.0	$\text{pA}/^{\circ}\text{C}$	
CMRR	Common Mode Rejection Ratio	$V_{CM} = \pm 13.5\text{V}$	●	110	128	108	128	dB	
PSRR	Power Supply Rejection Ratio	$V_S = \pm 1.5\text{V}$ to $\pm 20\text{V}$	●	110	126	108	126	dB	
Input Voltage Range			●	± 13.5		± 13.5		V	
V_{OUT}	Output Voltage Swing	$R_L = 10\text{k}\Omega$	●	± 13	± 14	± 13	± 14	V	
I_S	Supply Current		●	400	650	400	800	μA	

LT1012A/LT1012

ELECTRICAL CHARACTERISTICS

The ● denotes the specifications which apply over the full operating temperature range of $0^{\circ}\text{C} \leq T_A \leq 70^{\circ}\text{C}$. $V_S = \pm 15\text{V}$, $V_{CM} = 0\text{V}$, unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	LT1012AC			LT1012C			UNITS
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{OS}	Input Offset Voltage	(Note 3)	● ●	20 30	60 160	20 30	100 200	μV μV	
	Average Temperature Coefficient of Input Offset Voltage		●	0.2	0.6	0.2	1.0	$\mu\text{V}/^{\circ}\text{C}$	
I_{OS}	Input Offset Current	(Note 3)	● ●	25 40	230 300	35 45	230 300	pA pA	
	Average Temperature Coefficient of Input Offset Current		●	0.3	2.5	0.3	2.5	pA/ $^{\circ}\text{C}$	
I_B	Input Bias Current	(Note 3)	● ●	± 35 ± 50	± 230 ± 300	± 35 ± 50	± 230 ± 300	pA pA	
	Average Temperature Coefficient of Input Bias Current		●	0.3	2.5	0.3	2.5	pA/ $^{\circ}\text{C}$	
A_{VOL}	Large-Signal Voltage Gain	$V_{OUT} = \pm 12\text{V}$, $R_L \geq 10\text{k}\Omega$ $V_{OUT} = \pm 10\text{V}$, $R_L \geq 2\text{k}\Omega$	● ●	200 200	1500 1000	150 150	1500 800	V/mV V/mV	
CMRR	Common Mode Rejection Ratio	$V_{CM} = 13.5\text{V}$	●	110	130	108	130	dB	
PSRR	Power Supply Rejection Ratio	$V_S = \pm 1.3\text{V}$ to $\pm 20\text{V}$	●	110	128	108	128	dB	
	Input Voltage Range		●	± 13.5			± 13.5		V
V_{OUT}	Output Voltage Swing	$R_L = 10\text{k}\Omega$	●	± 13	± 14	± 13	± 14	V	
I_S	Supply Current		●	400	600	400	800	μA	

ELECTRICAL CHARACTERISTICS

The ● denotes the specifications which apply over the full operating temperature range of $0^{\circ}\text{C} \leq T_A \leq 70^{\circ}\text{C}$. $V_S = \pm 15\text{V}$, $V_{CM} = 0\text{V}$, unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS	LT1012D			LT1012S8			UNITS
			MIN	TYP	MAX	MIN	TYP	MAX	
V_{OS}	Input Offset Voltage	(Note 3)	● ●	25 40	140	30 45	200 270	μV μV	
	Average Temperature Coefficient of Input Offset Voltage		●	0.3	1.7	0.3	1.8	$\mu\text{V}/^{\circ}\text{C}$	
I_{OS}	Input Offset Current	(Note 3)	● ●	35 45	380	60 80	380 500	pA pA	
	Average Temperature Coefficient of Input Offset Current		●	0.35	4.0	0.4	4.0	pA/ $^{\circ}\text{C}$	
I_B	Input Bias Current	(Note 3)	● ●	± 50 ± 65	± 420	± 100 ± 150	± 420 ± 550	pA pA	
	Average Temperature Coefficient of Input Bias Current		●	0.4	5.0	0.5	5.0	pA/ $^{\circ}\text{C}$	
A_{VOL}	Large-Signal Voltage Gain	$V_{OUT} = \pm 12\text{V}$, $R_L \geq 10\text{k}\Omega$ $V_{OUT} = \pm 10\text{V}$, $R_L \geq 2\text{k}\Omega$	● ●	150 150	1500 800	150 100	1500 800	V/mV V/mV	
CMRR	Common Mode Rejection Ratio	$V_{CM} = \pm 13.5\text{V}$	●	108	130	108	130	dB	
PSRR	Power Supply Rejection Ratio	$V_S = \pm 1.3\text{V}$ to $\pm 20\text{V}$	●	108	128	108	128	dB	
	Input Voltage Range		●	± 13.5		± 13.5		V	
V_{OUT}	Output Voltage Swing	$R_L = 10\text{k}\Omega$	●	± 13	± 14	± 13	± 14	V	
I_S	Supply Current		●	400	800	400	800	μA	


Note 1: Absolute Maximum Ratings are those values beyond which the life of a device may be impaired.

Note 2: Differential input voltages greater than 1V will cause excessive current to flow through the input protection diodes unless limiting resistance is used.

Note 3: These specifications apply for $V_{MIN} \leq V_S \leq \pm 20\text{V}$ and $-13.5\text{V} \leq V_{CM} \leq 13.5\text{V}$ (for $V_S = \pm 15\text{V}$). $V_{MIN} = \pm 1.2\text{V}$ at 25°C , $\pm 1.3\text{V}$ from 0°C to 70°C , $\pm 1.5\text{V}$ from -55°C to 125°C .

Note 4: 10Hz noise voltage density is sample tested on every lot. Devices 100% tested at 10Hz are available on request.

Note 5: This parameter is tested on a sample basis only.



Optional Offset Nulling and Overcompensation Circuits


Input offset voltage can be adjusted over a $\pm 800\mu\text{V}$ range with a 5k to 100k potentiometer.

The LT1012 is internally compensated for unity gain stability. The overcompensation capacitor, C_S , can be used to improve capacitive load handling capability, to narrow noise bandwidth, or to stabilize circuits with gain in the feedback loop.

LT1012A/LT1012


TYPICAL PERFORMANCE CHARACTERISTICS

Offset Voltage vs Source Resistance (Balanced or Unbalanced)




LT1012A • TPC01

Typical Distribution of Input Bias Current




LT1012A • TPC02

Typical Distribution of Input Offset Current




LT1012A • TPC03

Input Bias Current vs Temperature




LT1012A • TPC04

Input Bias Current Over Common Mode Range




LT1012A • TPC05




LT1012 • TPC06

Warm-Up Drift




LT1012A • TPC07

Long Term Stability of Four Representative Units



LT1012A • TPC08

Offset Voltage Drift with Temperature of Four Representative Units




LT1012A • TPC09

sn1012 1012afbs


TYPICAL PERFORMANCE CHARACTERISTICS

0.1Hz to 10Hz Noise




LT1012A • TPC10

Noise Spectrum




LT1012A • TPC11

Total Noise vs Source Resistance




LT1012A • TPC12

Supply Current vs Supply Voltage




LT1012A • TPC13

Common Mode Rejection vs Frequency




LT1012A • TPC14

Power Supply Rejection vs Frequency




LT1012A • TPC15

Voltage Gain vs Frequency




LT1012A • TPC16

Gain, Phase Shift vs Frequency



LT1012A • TPC17

Voltage Gain vs Load Resistance




LT1012A • TPC18


LT1012A/LT1012

TYPICAL PERFORMANCE CHARACTERISTICS


Small-Signal Transient Response




Small-Signal Transient Response



Large-Signal Transient Response




Output Short-Circuit Current vs Time




LT1012A • TPC019

Slew Rate, Gain Bandwidth Product vs Overcompensation Capacitor




LT1012A • TPC20

Closed-Loop Output Impedance




LT1012A • TPC21

Common Mode Range and Voltage Swing at Minimum Supply Voltage



LT1012A • TPC22

Minimum Supply Voltage, Voltage Gain at V_{MIN}



LT1012A • TPC23

APPLICATIONS INFORMATION


The LT1012 may be inserted directly into OP-07, LM11, 108A or 101A sockets with or without removal of external frequency compensation or nulling components. The LT1012 can also be used in 741, LF411, LF156 or OP-15 applications provided that the nulling circuitry is removed.

Although the OP-97 is a copy of the LT1012, the LT1012 directly replaces and upgrades OP-97 applications. The LT1012C and D have lower offset voltage and drift than the OP-97F. The LT1012A has lower supply current than the OP-97A/E. In addition, all LT1012 grades guarantee operation at $\pm 1.2V$ supplies.

Achieving Picoampere/Microvolt Performance

In order to realize the picoampere/microvolt level accuracy of the LT1012, proper care must be exercised. For example, leakage currents in circuitry external to the op amp can significantly degrade performance. High quality insulation should be used (e.g. Teflon, Kel-F); cleaning of all insulating surfaces to remove fluxes and other residues will probably be required. Surface coating may be necessary to provide a moisture barrier in high humidity environments.

Board leakage can be minimized by encircling the input circuitry with a guard ring operated at a potential close to that of the inputs: in inverting configurations the guard ring should be tied to ground, in non-inverting connections to the inverting input at Pin 2. Guarding both sides of the printed circuit board is required. Bulk leakage reduction depends on the guard ring width. Nanoampere level leakage into the offset trim terminals can affect offset voltage and drift with temperature.



LT1012A * A101

Microvolt level error voltages can also be generated in the external circuitry. Thermocouple effects caused by temperature gradients across dissimilar metals at the contacts to the input terminals can exceed the inherent drift of the amplifier. Air currents over device leads should be minimized, package leads should be short, and the two input leads should be as close together as possible and maintained at the same temperature.

Noise Testing

For application information on noise testing and calculations, please see the LT1008 data sheet.

Frequency Compensation

The LT1012 can be overcompensated to improve capacitive load handling capability or to narrow noise bandwidth. In many applications, the feedback loop around the amplifier has gain (e.g. logarithmic amplifiers); overcompensation can stabilize these circuits with a single capacitor.

The availability of the compensation terminal permits the use of feedforward frequency compensation to enhance slew rate. The voltage follower feedforward scheme bypasses the amplifier's gain stages and slews at nearly $10V/\mu s$.


The inputs of the LT1012 are protected with back-to-back diodes. Current limiting resistors are not used, because the leakage of these resistors would prevent the realization of picoampere level bias currents at elevated temperatures. In the voltage follower configuration, when the input is driven by a fast, large signal pulse ($>1V$), the input protection diodes effectively short the output to the input during slewing, and a current, limited only by the output short-circuit protection will flow through the diodes.

The use of a feedback resistor, as shown in the voltage follower feedforward diagram, is recommended because this resistor keeps the current below the short-circuit limit, resulting in faster recovery and settling of the output.

LT1012A/LT1012

APPLICATIONS INFORMATION


Test Circuit for Offset Voltage and its Drift with Temperature



*RESISTORS MUST HAVE LOW THERMOELECTRIC POTENTIAL


LT1012A • AI02

Follower Feedforward Compensation



LT1012A • AI03


Pulse Response of Feedforward Compensation



5V/DIV

TYPICAL APPLICATIONS

Ammeter with Six Decade Range



Q1, Q2, Q3, Q4, RCA CA3146 TRANSISTOR ARRAY.
CALIBRATION: ADJUST R1 FOR FULL-SCALE DEFLECTION WITH 1μA INPUT CURRENT


AMPMETER MEASURES CURRENTS FROM 100pA TO 100μA WITHOUT THE USE OF EXPENSIVE HIGH VALUE RESISTORS. ACCURACY AT 100μA IS LIMITED BY THE OFFSET VOLTAGE BETWEEN Q1 AND Q2 AND, AT 100pA, BY THE INVERTING BIAS CURRENT OF THE LT1012

LT1012A • TA03

sn1012 1012afbs

TYPICAL APPLICATIONS


Saturated Standard Cell Amplifier



THE TYPICAL 30pA BIAS CURRENT OF THE LT1012 WILL DEGRADE THE STANDARD CELL BY ONLY 1ppm/YEAR.
NOISE IS A FRACTION OF A ppm. UNPROTECTED GATE MOSFET ISOLATES STANDARD CELL ON POWER DOWN

LT1012A • TA05

Amplifier for Bridge Transducers




LT1012A • TA06

sn1012 1012afbs

LT1012A/LT1012


TYPICAL APPLICATIONS

Amplifier for Photodiode Sensor




LT1012A • TA07

Buffered Reference for A-to-D Converters




LT1012A • TA08

Instrumentation Amplifier with $\pm 100V$ Common Mode Range



LT1012A • TA09

Low Power Comparator with $<10\mu V$ Hysteresis




LT1012A • TA10

sn1012 1012afbs

TYPICAL APPLICATIONS


Air Flow Detector



MOUNT R1 IN AIRFLOW.
ADJUST R2 SO OUTPUT GOES
HIGH WHEN AIRFLOW STOPS

LT1012A • TA11

Input Amplifier for 4.5 Digit Voltmeter




* RATIO MATCH $\pm 0.01\%$

THIS APPLICATION REQUIRES LOW
BIAS CURRENT AND OFFSET VOLTAGE,
LOW NOISE, AND LOW DRIFT WITH
TIME AND TEMPERATURE


LT1012A • TA12

Resistor Multiplier



LT1012 • TA13

"No Trims" 12-Bit Multiplying DAC Output Amplifier




WHEN THE REFERENCE INPUT DROPS TO 0.1V,
THE LEAST SIGNIFICANT BIT DECREASES TO
THE MICROVOLT/PICOAMPERE RANGE

LT1012 • TA14

sn1012 1012afbs

LT1012A/LT1012


SCHEMATIC DIAGRAM



LT1012A • SD01

sn1012 1012afbs


PACKAGE DESCRIPTION



LT1012A/LT1012

PACKAGE DESCRIPTION

N8 Package
8-Lead PDIP (Narrow .300 Inch)
(Reference LTC DWG # 05-08-1510)




NOTE:

1. DIMENSIONS ARE INCHES
MILLIMETERS

*THESE DIMENSIONS DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS.
MOLD FLASH OR PROTRUSIONS SHALL NOT EXCEED .010 INCH (0.254mm)

PACKAGE DESCRIPTION


S8 Package
8-Lead Plastic Small Outline (Narrow .150 Inch)
(Reference LTC DWG # 05-08-1610)



LT1012A/LT1012

TYPICAL APPLICATION

Kelvin-Sensed Platinum Temperature Sensor Amplifier



* = WIRE WOUND RESISTORS
ALL OTHER RESISTORS ARE 1% METAL FILM
TRIM R2 AT 0°C FOR $V_0 = 0V$
TRIM R3 AT 100°C FOR $V_0 = 10V$
TRIM R4 AT 50°C FOR $V_0 = 5V$
IN THE ORDER INDICATED

POSITIVE FEEDBACK (R1) LINEARIZES THE
INHERENT PARABOLIC NONLINEARITY OF
THE PLATINUM SENSOR AND REDUCES
ERRORS FROM 1.2°C TO 0.004°C OVER
THE -50°C TO 150°C RANGE

LT1012A • TA04