



Low Voltage Avalanche 500 mW Zener Diodes

Qualified per MIL-PRF-19500/437

Qualified Levels:
JAN, JANTX and
JANTXV


DESCRIPTION

The 1N5518BUR-1 thru 1N5546BUR-1 series of 0.5 watt glass surface mount Zener voltage regulators provides a selection from 3.3 to 33 volts with tolerances ranging from plus/minus 1% to 10%. The standard tolerance is plus/minus 5% with the B suffix unless ordered otherwise. These glass surface mount devices feature an internal metallurgical bond. This type of bonded Zener package construction is also available in JAN, JANTX, and JANTXV military qualifications. Microsemi also offers numerous other Zener products to meet higher and lower power applications.

Important: For the latest information, visit our website <http://www.microsemi.com>.

FEATURES

- JEDEC registered 1N5518 thru 1N5546 series.
- Voltage tolerances of plus/minus 10%, 5%, 2%, and 1% available. See [Note 1](#) on page 3.
- Internal metallurgical bond.
- JAN, JANTX, and JANTXV qualification per MIL-PRF-19500/437 available.
- RoHS compliant versions available (commercial grade only).



**DO-213AA MELF
Package**

Also available in:

 **DO-35 (DO-204AH)**
(axial-leaded)
[1N5518B-1 thru 1N5546B-1](#)

APPLICATIONS / BENEFITS

- Regulates voltage over a broad operating current and temperature range.
- Extensive selection from 3.3 to 33 V.
- Hermetically sealed surface mount package.
- Non-sensitive to ESD per MIL-STD-750 Method 1020.
- Minimal capacitance (see [Figure 3](#)).
- Inherently radiation hard as described in Microsemi's "[MicroNote 050](#)" which is available at microsemi.com.

MAXIMUM RATINGS

Parameters/Test Conditions	Symbol	Value	Unit
Junction and Storage Temperature	T _J and T _{STG}	-65 to +175	°C
Steady-State Power ⁽¹⁾ (Also see derating in Figure 2)	P _D	0.5	W
Thermal Resistance Junction-to-End Cap ⁽²⁾	R _{θJEC}	100	°C/W
Thermal Resistance Junction-to-Ambient ⁽²⁾	R _{θJA}	300	°C/W
Thermal Impedance	Z _{θJX}	35	°C/W
Forward Voltage @ 200 mA	V _F	1.1	V
Solder Pad Temperature @ 10 s	T _{SP}	260	°C

- Notes:**
- At end cap temperature T_{EC} ≤ 125 °C or at ambient T_A ≤ 50 °C when mounted on FR4 PC board as described for thermal resistance above (see [Figure 2](#) for derating). Derate to 0 at +175 °C.
 - When mounted on FR4 PC board (1 oz Cu) with recommended footprint (see last page).

MSC – Lawrence

6 Lake Street,
Lawrence, MA 01841
1-800-446-1158
(978) 620-2600
Fax: (978) 689-0803

MSC – Ireland

Gort Road Business Park,
Ennis, Co. Clare, Ireland
Tel: +353 (0) 65 6840044
Fax: +353 (0) 65 6822298


Website:

www.microsemi.com

MECHANICAL and PACKAGING

- CASE: Hermetically sealed glass DO-213AA (SOD80 or MLL34) MELF style package.
- TERMINALS: End caps tin-lead plated or RoHS compliant matte-tin plating available (on commercial only) solderable per MIL-STD-750, method 2026.
- POLARITY: Cathode indicated by band where diode is to be operated with the banded end positive with respect to the opposite end for Zener regulation.
- MOUNTING SURFACE SELECTION: The Axial Coefficient of Expansion (COE) of this device is approximately +6 PPM/ $^{\circ}$ C. The COE of the Mounting Surface System should be selected to provide a suitable match with this device.
- MARKING: Cathode band only.
- TAPE & REEL option: Standard per EIA-481-1-A with 12 mm tape (add "TR" suffix to part number). Consult factory for quantities.
- WEIGHT: 0.04 grams.
- See [Package Dimensions](#) on last page.

PART NOMENCLATURE



SYMBOLS & DEFINITIONS

Symbol	Definition
I_R	Reverse Current: The maximum reverse (leakage) current that will flow at the specified voltage and temperature.
I_z , I_{zT} , I_{zK}	Regulator Current: The dc regulator current (I_z), at a specified test point (I_{zT}), near breakdown knee (I_{zK}).
I_{zL}	Low Regulator (Zener) Current: The lowest rated dc current for the specified power rating.
I_{zM}	Maximum Regulator (Zener) Current: The maximum rated dc current for the specified power rating.
V_z	Zener Voltage: The Zener voltage the device will exhibit at a specified current (I_z) in its breakdown region.
ΔV_z	Voltage Regulation: The change in Zener voltage between two specified currents or percentage of I_{zM} .
Z_{zT} or Z_{zK}	Dynamic Impedance: The small signal impedance of the diode when biased to operate in its breakdown region at a specified rms current modulation (typically 10% of I_{zT} or I_{zK}) and superimposed on I_{zT} or I_{zK} respectively.

ELECTRICAL CHARACTERISTICS
 $(T_A = 25^\circ C$ unless otherwise noted. Based on dc measurements at thermal equilibrium; $V_F = 1.1$ Max @ $IF = 200$ mA for all types.)

JEDEC TYPE NUMBER (Note 1)	NOMINAL ZENER VOLTAGE V_Z @ I_{ZT} (Note 2)	TEST CURRENT I_{ZT}	(B-C-D Suffix Only) MAX. ZENER IMPEDANCE Z_{ZT} @ I_{ZT} (Note 3)	MAX. REVERSE CURRENT (Note 4)			(B-C-D Suffix Only) MAXIMUM dc ZENER CURRENT I_{ZM} (Note 5)	(B-C-D Suffix Only) MAX. NOISE DENSITY AT $I_Z = 250$ μA N_D	REGULATION FACTOR ΔV_Z (Note 6)	LOW V_Z CURRENT I_{ZL} (Note 6)				
				I_R	V _R – VOLTS									
					A Suffix only	B-C-D Suffix only								
Volts	mA	Ohms	μA											
1N5518BUR-1	3.3	20	26	5.0	0.90	1.0	115	0.5	0.90	2.0				
1N5519BUR-1	3.6	20	24	3.0	0.90	1.0	105	0.5	0.90	2.0				
1N5520BUR-1	3.9	20	22	1.0	0.90	1.0	98	0.5	0.85	2.0				
1N5521BUR-1	4.3	20	18	3.0	1.0	1.5	88	0.5	0.75	2.0				
1N5522BUR-1	4.7	10	22	2.0	1.5	2.0	81	0.5	0.60	1.0				
1N5523BUR-1	5.1	5.0	26	2.0	2.0	2.5	75	0.5	0.65	0.25				
1N5524BUR-1	5.6	3.0	30	2.0	3.0	3.5	68	1.0	0.30	0.25				
1N5525BUR-1	6.2	1.0	30	1.0	4.5	5.0	61	1.0	0.20	0.01				
1N5526BUR-1	6.8	1.0	30	1.0	5.5	6.2	56	1.0	0.10	0.01				
1N5527BUR-1	7.5	1.0	35	0.5	6.0	6.8	51	2.0	0.05	0.01				
1N5528BUR-1	8.2	1.0	40	0.5	6.5	7.5	46	4.0	0.05	0.01				
1N5529BUR-1	9.1	1.0	45	0.1	7.0	8.2	42	4.0	0.05	0.01				
1N5530BUR-1	10.0	1.0	60	0.05	8.0	9.1	38	4.0	0.10	0.01				
1N5531BUR-1	11.0	1.0	80	0.05	9.0	9.9	35	5.0	0.20	0.01				
1N5532BUR-1	12.0	1.0	90	0.05	9.5	10.8	32	10	0.20	0.01				
1N5533BUR-1	13.0	1.0	90	0.01	10.5	11.7	29	15	0.20	0.01				
1N5534BUR-1	14.0	1.0	100	0.01	11.5	12.6	27	20	0.20	0.01				
1N5535BUR-1	15.0	1.0	100	0.01	12.5	13.5	25	20	0.20	0.01				
1N5536BUR-1	16.0	1.0	100	0.01	13.0	14.4	24	20	0.20	0.01				
1N5537BUR-1	17.0	1.0	100	0.01	14.0	15.3	22	20	0.20	0.01				
1N5538BUR-1	18.0	1.0	100	0.01	15.0	16.2	21	20	0.20	0.01				
1N5539BUR-1	19.0	1.0	100	0.01	16.0	17.1	20	20	0.20	0.01				
1N5540BUR-1	20.0	1.0	100	0.01	17.0	18.0	19	20	0.20	0.01				
1N5541BUR-1	22.0	1.0	100	0.01	18.0	19.8	17	25	0.25	0.01				
1N5542BUR-1	24.0	1.0	100	0.01	20.0	21.6	16	30	0.30	0.01				
1N5543BUR-1	25.0	1.0	100	0.01	21.0	22.4	15	35	0.35	0.01				
1N5544BUR-1	28.0	1.0	100	0.01	23.0	25.2	14	40	0.40	0.01				
1N5545BUR-1	30.0	1.0	100	0.01	24.0	27.0	13	45	0.45	0.01				
1N5546BUR-1	33.0	1.0	100	0.01	28.0	29.7	12	50	0.50	0.01				

NOTES:
1. TOLERANCE AND VOLTAGE DESIGNATION –

The JEDEC type numbers with "A" prior to the UR-1 suffix are +/-10% with guaranteed limits for V_Z , I_R , and V_F . Units with guaranteed limits for all six parameters are indicated by a B suffix for +/-5.0% units, C suffix for +/-2.0% and D suffix for +/-1.0% prior to the UR-1 suffix.

2. ZENER VOLTAGE (V_Z) MEASUREMENT –

Nominal Zener voltage is measured with the device junction in thermal equilibrium with ambient temperature of 25 °C.

3. ZENER IMPEDANCE (Z_Z) MEASUREMENT –

The Zener impedance is derived from the 60 Hz ac voltage, which results when an ac current having an rms value equal to 10% of the dc Zener current (I_{ZT}) is superimposed on I_{ZT} .

4. REVERSE CURRENT (I_R) –

Reverse currents are guaranteed and are measured at V_R as shown on the table.

5. MAXIMUM REGULATOR CURRENT (I_{ZM}) –


The maximum current shown is as shown in MIL-PRF-19500/437.

6. MAXIMUM REGULATION FACTOR (ΔV_Z) –




ΔV_Z is the maximum difference between V_Z at I_{ZT} and V_Z at I_{ZL} measured with the device junction in thermal equilibrium.

GRAPHS

Noise density, (N_D) is specified in microvolt-rms per square-root-hertz. Actual measurement is performed using a 1 kHz to 3 kHz frequency bandpass filter at a constant Zener test current (I_{ZT}) at 25 °C ambient temperature.


FIGURE 1

Noise Density Measurement Circuit


FIGURE 2 – Power Derating Curve

FIGURE 3 – Capacitance vs. Zener Voltage (typical)

FIGURE 4
Zener Diode Characteristics and Symbol Identification



GRAPHS (continued)

FIGURE 5
Zener Impedance vs. Operation Current (typical)

PACKAGE DIMENSIONS




Ltr	Dimensions			
	Inch		Millimeter	
	Min	Max	Min	Max
BD	.063	.067	1.60	1.70
BL	.130	.146	3.30	3.71
ECT	.016	.022	0.41	0.56
S	.001 min		0.03 min	

NOTES:

1. Dimensions are in inch.
2. Millimeters are given for general information only.
3. In accordance with ASME Y14.5M, diameters are equivalent to Φx symbology.

PAD LAYOUT



	INCHES	mm
A	.200	5.08
B	.055	1.40
C	.080	2.03