

Fluke 355/353 True-rms 2000 A Clamp Meters

Technical Data

High current and a large jaw, make these clamps well suited for industrial and utility applications

Confidently take reliable readings with the true-rms, Fluke 355/353 Clamp Meters; the tools of choice for high-current measurements up to 2000 A. The extra-wide jaw easily clamps around large conductors typically found in high-current applications. The rugged design and CAT IV 600 V, CAT III 1000 V ratings, add an extra element of protection when taking high-powered measurements.

Accurate peak measurements can be taken using the in-rush current mode, ideal for motors and inductive loads. The 355 also measures voltage and resistance, making this the most versatile tool for utilities, electrical contractors, and industrial service technicians.



- Reliably handle a wide range of high-current applications with 2000 A ac + dc true-rms, 1400 A ac, and 2000 A dc
- The large 58 mm (2.3 in) jaw capacity is suitable for large, or multiple conductors
- CAT IV 600 V, CAT III 1000 V rating for added user protection
- In-rush current measurement captures 'power-on' surge current with accuracy and repeatability
- High voltage measurement of 1000 V ac + dc true-rms, 600 V ac, and 1000 V dc allows users to perform multiple tests with only one tool (355 only)
- Resistance to 400 k Ω coupled with a continuity beeper, provide the convenience of a multimeter (355 only)
- Accurately measure frequency up to 1 kHz for optimum troubleshooting
- Quickly analyze readings using the MIN, MAX, and AVG functions
- A large backlit display allows for easy visibility in low-lit areas
- Use the display hold feature to capture readings even when the display cannot be viewed
- Use the low-pass filter to smooth out noisy loads and stabilize readings



Specifications

Electrical specifications

Current measurement dc and ac 10 Hz to 100 Hz

Range	Resolution	Accuracy, A	Trigger Level for Inrush	Trigger Level for Hz Filter OFF	Trigger Level for Hz Filter ON
40 A	10 mA	1.5 % rdg + 15 digits	0.50 A	2.50 A	0.50 A
400 A	100 mA	1.5 % rdg + 5 digits	5.0 A	2.5 A	2.5 A
2000 A; 1400 ac rms	1 A	1.5 % rdg + 5 digits	5 A	8 A	8 A

Crest Factor (50/60 Hz)

Range	Crest Factor*
40 A	2 @ 33 A, 2.4 @ 27 A
400 A	2 @ 330 A, 2.4 @ 270 A
2000 A; 1400 ac rms	2 @ 1000 A, 2.4 @ 833 A

*Add 2 % to error spec for CF > 2

Current measurement ac 100.1 Hz to 1 kHz

Range	Resolution	Accuracy > 10 A	Trigger Level for Inrush	Trigger Level for Hz Filter OFF	Trigger Level for Hz Filter ON
40 A	10 mA	3.5 % rdg + 15 digits	0.50 A	2.50 A	0.50 A
400 A	100 mA	3.5 % rdg + 5 digits	5.0 A	2.5 A	2.5 A
2000 A; 1400 ac rms	1 A	3.5 % rdg + 5 digits	5 A	8 A	8 A

Voltage measurement (355 only) dc and ac 10 Hz to 100 Hz

600 V and 1000 V ranges have 10 % over range to 660 V and 1100 V respectively.

Range	Resolution	Accuracy	Trigger Level for Hz Filter OFF	Trigger Level for Hz Filter ON
4 V	1 mV	1 % rdg + 10 digits	0.050 V	0.050 V
40 V	10 mV	1 % rdg + 5 digits	0.25 V	0.25 V
400 V	100 mV	1 % rdg + 5 digits	6 V	6 V
600 V ac rms	1 V	1 % rdg + 5 digits	6 V	6 V
1000 V dc	1 V	1 % rdg + 5 digits	N/A	N/A

Voltage measurement (355 only) ac 100.1 Hz to 1 kHz

600 V and 1000 V ranges have 10 % over range to 660 V and 1100 V respectively.

Range	Resolution	Accuracy	Trigger Level for Hz Filter OFF	Trigger Level for Hz Filter ON
4 V	1 mV	3 % rdg + 10 digits	0.050 V	0.050 V
40 V	10 mV	3 % rdg + 5 digits	0.25 V	0.25 V
400 V	100 mV	3 % rdg + 5 digits	6 V	6 V
600 V ac rms	1 V	3 % rdg + 5 digits	6 V	6 V

Ohms measurement (355 only)

Range	Resolution	Accuracy
400 Ω	0.1 Ω	1.5 % + 5 digits
4 kΩ	1 Ω	1.5 % + 5 digits
40 kΩ	10 Ω	1.5 % + 5 digits
400 kΩ	100 Ω	1.5 % + 5 digits

Continuity beeper (355 only)

On at $\leq 30 \Omega$
Off at $\geq 100 \Omega$

Frequency measurement

Measurement range	5.0 Hz to 1 kHz
Resolution	0.1 Hz (15 Hz to 399.9 Hz); 1 Hz (400 Hz to 1 kHz)
Accuracy – 5.0 Hz to 100 Hz	0.2 % + 2 counts
Accuracy – 100.1 Hz to 1 kHz	0.5 % + 5 counts
Trigger level	Refer to current and voltage tables

General specifications

Batteries	Six 1.5 V AA NEDA 15 A or IEC LR6
Battery life (with typical usage, backlight off)	100 hours
Test leads	Rated to 1000 V
Weight	.814 kg (1.8 lb)
Jaw size	58 mm (2.28 in)
Dimensions (LxWxD)	300 mm x 98 mm x 52 mm (12 in x 3.75 in x 2 in)
Safety rating	IEC 61010-2-032, 600 V CAT IV, 1000 V CAT III

Environmental specifications

Operating temperature	32 °F to + 122 °F (0 °C to +50 °C)
Storage temperature	-4 °F to 140 °F (-20 °C to +60 °C)
Operating humidity	0 to 95 % (non-condensing)
Operating altitude	2000 m
Storage altitude	10,000 m
IP rating	42 (indoor use only)
Drop test requirements	1 m
EMI, RFI, EMC	FCC part 15, IEC/EN 61326-1:1997 class B, IEC/EN 61326:1997 3V/m, performance criteria B, EN61325
Temperature coefficients	Current: 0.1 % of reading per °C outside 22 °C to 24 °C Voltage: 0.1 % of reading per °C outside 22 °C to 24 °C

Ordering information:

Fluke-353 AC/DC True-rms Clamp Meter, 2000 A, Amps only

Includes: C43 Soft Carrying Case, 6 AA batteries, and users manual

Fluke-355 AC/DC True-rms Clamp Meter, 2000 A

Includes: C43 Soft Carrying Case, 6 AA batteries, TL224 1.5 m Silicone Rubber Test Leads, TP2 Test Probes, AC285 Alligator Clips, and users manual



Fluke-355



Fluke-353

Fluke. *Keeping your world up and running.®*

Fluke Corporation

PO Box 9090, Everett, WA USA 98206

Fluke Europe B.V.
PO Box 1186, 5602 BD
Eindhoven, The Netherlands

For more information call:
In the U.S.A. (800) 443-5853 or
Fax (425) 446-5116
In Europe/M-East/Africa +31 (0) 40 2675 200 or
Fax +31 (0) 40 2675 222
In Canada (800) 36-FLUKE or
Fax (905) 890-6866
From other countries +1 (425) 446-5500 or
Fax +1 (425) 446-5116
Web access: <http://www.fluke.com>

©2007 Fluke Corporation.
Specifications subject to change without notice.
Printed in U.S.A. 9/2007 3094045 D-EN-N Rev A



DOMINION



**CARTA DE DISTRIBUIDOR AUTORIZADO
FLUKE y AMPROBE**



FLUKE®

Ciudad de México, Enero 2023.

A quien corresponda:

Por medio del presente, Mexicana de Electrónica Industrial. S.A. de C.V., conocida como **Dominion México** y Master Distributor exclusivo de la marca **Fluke y Amprobe** en México, informa que la compañía **AG ELECTRONICA SAPI DE CV** es nuestro **Distribuidor Autorizado** de las herramientas de medición marca **Fluke, Amprobe, PLS y Comark** durante el 2023.

Las herramientas de la marca Fluke, que Mexicana de Electrónica Industrial S.A. de C.V. surte a **AG ELECTRONICA SAPI DE CV** cuentan con las **Garantías Originales de Fluke en México**, así como con la mejor capacitación y el mejor soporte técnico que proporcionamos en México.

Por cualquier aclaración o apoyo necesario relacionado con el anterior, quedamos a sus órdenes.

Teniendo validez al 31 de diciembre de 2023, extensiva a renovación.

Atentamente:

ADMINISTRACIÓN DEL PORTAFOLIO



Av. Insurgentes Sur 810 Piso 10, 03100 Ciudad de México,
Teléfono: +52 55 5340 1400

DOMINION

**FLUKE®**

Estimado **Usuario Fluke.**

Mexicana De Electrónica Industrial SA de CV (parte del corporativo Dominion Global) somos el **único Master Distribuidor de la marca Fluke en México.**

Le informamos:

Los instrumentos Fluke cuentan con todos los beneficios de la protección de la garantía original del fabricante **sólo cuando se compran a través de un distribuidor local autorizado en México.**

Para asegurarse de que sus productos Fluke son auténticos, nuevos, de la más alta calidad y que cuentan con todos los permisos legales, autorizaciones o licencias exigibles en México (garantía original y local, cumplimiento de varios NOMs, permisos del IFT, etc.), cómprelos sólo a través de un **distribuidor local autorizado.**

Mercado gris

Existen vendedores y comercios del “mercado gris” que ofrecen productos Fluke a precios competitivos. Sin embargo, usted debe saber que los **vendedores del “mercado gris” carecen de la capacidad y competencia necesarias para proporcionar un servicio de garantía local, entregar la documentación/certificación legal, proporcionar asistencia post venta así como soporte técnico sobre el producto.** Desgraciadamente, algunos de estos comercios venden productos refabricados, de procedencia ilegal o de imitación.

Garantía

Los servicios de garantía, las reparaciones gratuitas en garantía y otros servicios de soporte proporcionados por Fluke, sólo pueden obtenerse en el país de compra original, a través de un distribuidor Fluke local autorizado.

Fluke podría cobrar al cliente los costos de importación y reexportación, la mano de obra y las piezas de repuesto, cuando un producto adquirido en un país se somete a reparación en otro país. En los casos necesarios, la verificación de la procedencia del producto Fluke se realizará mediante su número de serie.

Si necesita ayuda para encontrar/verificar a un distribuidor autorizado cerca de usted, envíe su consulta por correo electrónico a apoyoaventas@dominion.mx

Si no reside en México, por favor diríjase al representante autorizado que corresponde a su país, o bien ingrese a la página <https://www.distribuidoresfluke.mx/proteja-su-compra/>

Proteja su inversión y aproveche de todos los beneficios que le otorga Fluke a través de sus Distribuidores Autorizados en México.

DOMINION