

TOSHIBA INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP

TOSHIBA BIPOLAR LINEAR INTEGRATED CIRCUIT
SILICON MONOLITHIC

Unit in mm

5.8W DUAL AUDIO POWER AMPLIFIER.

19W BTL AUDIO POWER AMPLIFIER.

The TA7240AP/TA7241AP are dual audio power amplifier for consumer applications. It is designed for high power, low distortion and low noise.

It also contains various kind of protectors.

It is suitable for car-audio power amplifier with high performance.

- Two Kinds of Pin Configuration are Available :
Normal (TA7240AP) and Reverse (TA7241AP) for Easier Layout Design of Pc-board when Used in BTL-Stereo Application.

- Operating Supply Voltage Range : $V_{CC(opr)} = 9 \sim 18V$

- High Power

$V_{CC} = 13.2V$, $f = 1kHz$, $R_L = 4\Omega$

BTL	19W (Typ.)	THD=10%
	15W (Typ.)	THD=1%
DUAL	5.8W (Typ.)	THD=10%

- Low Distortion

$V_{CC} = 13.2V$, $f = 1kHz$, $R_L = 4\Omega$

BTL	0.03% (TYP.)	$P_{OUT} = 4W$, $G_V = 40dB$
DUAL	0.06% (TYP.)	$P_{OUT} = 1W$, $G_V = 52dB$


- Low Noise

$V_{CC} = 13.2V$, $R_L = 4\Omega$

BTL	0.14mV _{rms} (TYP.)	$G_V = 40dB$, $R_g = 0$, DIN NOISE : DIN 45405
DUAL	0.7mV _{rms} (TYP.)	$G_V = 52dB$, $R_g = 10k\Omega$, $BW = 20Hz \sim 20kHz$

- Protector : Thermal Shut Down, Over Voltage Protection.

BTL-OCL DC Short Protection.



The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication

or otherwise under any patent or patent rights of TOSHIBA or others.

TOSHIBA

INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP

MAXIMUM RATINGS (Ta=25°C)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Peak Supply Voltage (0.2 sec)	V _{CC} surge	45	V
DC Supply Voltage	V _{CC} DC	25	V
Operating Supply Voltage	V _{CC} opr	18	V
Output Current (peak)	I _O (peak)	4.5	A
Power Dissipation	P _D	25	W
Operating Temperature	T _{opr}	-30 ~ 75	°C
Storage Temperature	T _{stg}	-55 ~ 150	°C

ELECTRICAL CHARACTERISTICS

(Unless otherwise specified, V_{CC}=13.2V, R_L=4Ω, R_g=600Ω, f=1kHz, Ta=25°C)

CHARACTERISTIC	SYMBOL	TEST CIR-CUIT	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Quiescent Current	I _{CCQ}	2	V _{IN} =0	-	80	145	mA
BTL CONNECTION MODE	Output Power	P _{OUT} (1)	1 THD=10%	16	19	-	W
		P _{OUT} (2)	1 THD=1%	12	15	-	W
	Total Harmonic Distortion	THD(1)	1 P _{OUT} =4W, G _V =40dB	-	0.03	0.25	%
	Output Offset Voltage	V _{OFF}	1 V _{IN} =0	-	0	0.35	V
	Voltage Gain	G _V (1)	1 V _{OUT} =0dBm	-	40	-	dB
	Output Noise Voltage	V _{NO} (1)	1 R _g =0 DIN45405 Noise Filter	-	0.14	-	mV _{rms}
	Ripple Rejection Ratio	R.R(1)	1 f _{ripple} =100Hz V _{ripple} =0dBm	-	-52	-40	dB
DUAL MODE	Output Power	P _{OUT} (3)	2 THD=10%	5	5.8	-	W
	Total Harmonic Distortion	THD(2)	2 P _{OUT} =1W	-	0.06	0.30	%
	Voltage Gain	G _V (2)	2 V _{OUT} =0dBm	50	52	54	dB
	Voltage Gain Ratio	ΔG _V	2 V _{OUT} =0dBm	-1	0	1	dB
	Output Noise Voltage	V _{NO} (2)	2 R _g =10kΩ BW=20Hz ~ 20kHz	-	0.7	1.5	mV _{rms}
	Ripple Rejection Ratio	R.R(2)	2 f _{ripple} =100Hz V _{ripple} =0dBm	-	-52	-40	dB
	Cross Talk	C.T	2 V _{OUT} =0dBm	-	-57	-	dB
	Input Resistance	R _{IN}	2 f=1kHz	-	33	-	kΩ

TA7240AP-2

RATION

TOSHIBA

INTEGRATED CIRCUIT


TECHNICAL DATA

TA7240AP, TA7241AP


TEST CIRCUIT/APPLICATION CIRCUIT

TA7240AP

(1) BTL AMPLIFIER



(2) DUAL AMPLIFIER



TA7240AP-3

1989-4-4

TOSHIBA CORPORATION

www.agelectronica.com

TOSHIBA

INTEGRATED CIRCUIT


TECHNICAL DATA

TA7240AP, TA7241AP


TEST CIRCUIT/APPLICATION CIRCUIT

TA7241AP

(1) BTL AMPLIFIER



(2) DUAL AMPLIFIER



TA7240AP-4

1989-4-4

TOSHIBA CORPORATION

www.agelectronica.com

TOSHIBA

INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP

TYPICAL DC VOLTAGE OF EACH TERMINAL

(V_{CC}=13.2V, T_a=25°C, DUAL MODE TEST CIRCUIT)

TERMINAL No.		1	2	3	4	5	6	7	8	9	10	11	12
DC Voltage (V)	TA7240AP	1.5	1.5	4.4	GND	1.5	1.5	GND	6.6	12.7	V _{CC}	12.7	6.6
	TA7241AP	6.6	12.7	V _{CC}	12.7	6.6	GND	1.5	1.5	GND	4.4	1.5	1.5

APPLICATION INFORMATION

(This explanatory terminal number is for TA7240AP)

1. VOLTAGE GAIN

(1) Dual Mode

The closed loop voltage gain G_v is determined by R₁, R₂, R₃, R₄ and R_f.

$$G_v \div 20 \log \frac{R_2 + R_f + R_1}{R_f + R_1} + 20 \log \frac{R_3 + R_4}{R_4} \text{ (dB)}$$

when R_f=0, G_v=52dB(Typ.)

is given.

The recommended voltage gain is more than 40dB.




Fig. 1

(2) BTL Mode

The recommended BTL connection amplifier is shown in Figure 2.




Fig. 2

TA7240AP-5

1989-4-4

TOSHIBA CORPORATION

www.agelectronica.com

TOSHIBA

INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP

AMP.1 is noninverting amplifier and AMP.2 is inverting one. The output voltage is divided by resistors R₅ and R₆.

This divided voltage is applied to inverting input of AMP.2. R₅ and R₆ are determined in the following equation.

$$\frac{R_5+R_6}{R_5} = 20 \log \frac{R_1'+R_f'+R_2'}{R_1'+R_f'} + 20 \log \frac{R_3'+R_4'}{R_4'} \dots \text{Gv in Dual Mode}$$

The voltage gain in this circuit is 6dB higher than that in dual mode.

$$G_v = 20 \log \frac{R_1+R_f+R_2}{R_1+R_f} + 20 \log \frac{R_3+R_4}{R_4} + 6 \quad [\text{dB}]$$

In case of R_f=0

$$G_v = 52 + 6 = 58 [\text{dB}]$$

In case of R_f=750Ω

$$G_v = 34 + 6 = 40 [\text{dB}]$$

2. MUTING

Audio muting can be accomplished by connecting pin ③ (ripple filter) to GND as shown in Fig.3.

Then, the bias circuits are cut off.

Amount of muting attenuation is more than 60dB.

Precaution in muting operation is as follows.

- (1) The recovery time at muting off depends on Capacitance C₂, C₄ and C₅ in the test Circuit.
- (2) As this muting system is operated by the short-circuit of ripple filter : C₅, the ripple rejection ratio becomes worse in a muting mode.
Note that some "POP-Noise" occur when bias is shut off with mute-on.




Fig.3

3. CAPACITOR C₇, C₈

The purpose of capacitor C₇, C₈ is to prevent oscillation.

These capacitors need to be small temperature coefficient. So celamic capacitor is unsuitabel.

A voltage gain less than 40dB results occasionally in a parastic oscillation.

Stability for parastic oscillation is promoted by connecting capacitor of 500~1000pF between pin ① and pin ② (pin ⑤ and pin ⑥).

The additional capacitors are recommended to be inserted.

TA7240AP-6

1989-4-4

TOSHIBA CORPORATION

www.agelectronica.com

TOSHIBA

INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP

4. PRECAUTION AT PRINT BOARD DESIGN

- (1) Print Pattern board should be designed in consideration of stability for parastic oscillation.

The following parts-layout is recommended.

- 1st. Capacitors C6 and C10 are spaced most close to the output pin.
 - 2nd. Capacitor C7 or C8 is spaced close to the output pin next to C6 and C10.
 - 3rd. Capacitor C9 is spaced close to it next to C7 and C8.
 - 4th. Capacitor C11 is spaced close to it next to C9.
- (2) Input line (pin ⑥) and PW-GND line (pin ⑦) should not be spaced in parallel. In the paralld layout, output current signal in PW-GND line is bed back to input line by electromagnetic coupling. Then it deteriorates the total harmonic distortion, especially at high audio frequency region.
- (3) Undesirable terminating of capacitors deteriorates "pop" noise or THD. Capacitors C2, C4 and C5 should be terminated to Pre-GND (pin ④). Capacitors C7, C11, and C14 should be terminated to PW-GND (pin ⑦).
- (4) It is recommended to refer the standard print board.

TA7240AP-7

1989-4-4

TOSHIBA CORPORATION

www.agelectronica.com

TOSHIBA


INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP . TA7241P

STANDARD P.C.B

(TA7240AP BTL AMPLIFIER)



BOTTOM VIEW

TA7240AP-8

1989-4-4

TOSHIBA CORPORATION

www.agelectronica.com

TOSHIBA


INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP

STANDARD P.C.B

(TA7240AP DUAL AMPLIFIER)



BOTTOM VIEW

TA7240AP-9

1989-4-4





TOSHIBA CORPORATION

www.agelectronica.com

TOSHIBA INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP



TA7240AP-10

1989-4-4

TOSHIBA CORPORATION




www.agelectronica.com

TOSHIBA

INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP



TA7240AP-11

1989-4-4

TOSHIBA CORPORATION




www.agelectronica.com

TOSHIBA

INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP



TA7240AP-12

1989-4-4

TOSHIBA CORPORATION





www.agelectronica.com

TOSHIBA

INTEGRATED CIRCUIT

TECHNICAL DATA

TA7240AP, TA7241AP



TA7240AP-13*

1989-4-4

TOSHIBA CORPORATION

www.agelectronica.com