PRODUCT SPECIFICATION



Electrónica S.A. de C.V.

DMX DECODER&DRIVER SERIES

CT305R

SUMMARIZE

Thank you for using CT305R IR RGB LED Controller. With advanced micro-computer control technology,CT305R convert the widely used DMX512/1990 signal to analog signal.Can choose 1~3 output channel,256-level brightness control.For connecting of light console and analog device,or lighting&building lamps controlling.

Easily chose programs by IR controller or DMX controller.

FEATHERS

- Compatible with DMX512/1990
- 256-level brightness,full-color control
- a 3RGB Channel, 5A max. each
- 256 grey level,can express perfect effect
- 5 presaved color-changing programs
- Support IR remote control
- Can drive 1~3 channel of each lamp
- DMX addess setting freely
- Modularizing,can be combined with LED module neatly
- Can supply OEM board

Electrical Specifications

Channel. □ 3

Input Signal □ DMX-512/1990 digital signal

Output Signal □ 0~100% PWM dimming signal, can drive 5A(Each CH.)


Power Supply□ DC12V/24V

Power Output□ <200W
Remote Control Range: ≤10m
Operating Temp.□ 0~70□

Size□ 175(mm)*45(mm)*35(mm)□can be custom-made

Weight□ ≤300g

DIMENSION





Electrónica S.A. de C.V.