

**AU/EU/UK/US 24W Wall Charger 12.6V 1.5a Chargers Adapters for 3S 10.8V 11.1V
12V lithium ion batteries Electric Scooters battery Pack**

Quick Detail:

Brand Name:QUAWIN

Model Number:QW111-015-L

Use:3S 10.8V 11.1V 12V lithium ion or polymer battery pack

Type:Electric

Battery charger:automatic battery charger 12.6V

Color:Black

Shell Material:Plastic Shell(ABS+PC)

Input voltage:100-240VAC 50/60Hz

Output voltage:12.6V

Output current:1.5a(Max)

Output power:18.9W

Charge mode:CC—CV(Constant Current—Constant Voltage)

Output Connector: DC Plug 5.1.

Specifications:

3S 10.8V 11.1V 12V lithium ion battery pack

Features:

- Charging mode:CC—CV(Constant Current—Constant Voltage)
- High efficiency and low power consumption
- Stabilized output and low noise
- Efficiency(at 100% load): >=85%
- Operating temperature:-20°C ~ 45°C
- Storage temperature:-40°C ~ 85°C
- Operating humidity:5%~90%RH

Specification:

- Input: 100-240VAC 50/60Hz
- Output: DC 12.6V
- Charging current: 1.5a(Max)
- Dimensions (mm): 86*48*30.3
- Weight: 120±5g(only body)



Safety protections:

- Over Voltage protection
- Short Circuit protection
- Polarity error protection
- Over power protection
- Overheating protection

LED Indicator:

The charger turn trickle-off charging mode if battery is full (1/10C), and indicate by LED:

- Charging:Red LED
- Battery Full:Green LED

